

UNITED STATES PATENT APPLICATION

FOR

A MULTIPLE COIL PULL-IN COIL
FOR A SOLENOID ASSEMBLY
FOR A STARTER MOTOR ASSEMBLY

BY

DAVID A. FULTON
JAMES D. STUBER

RECEIVED
JUL 1 1994
FBI
WASHINGTON, DC

LAW OFFICES

FINNEGAN, HENDERSON,
FARABOW, GARRETT,
& DUNNER, L.L.P.
1300 I STREET, N.W.
WASHINGTON, DC 20005
202-408-4000

DESCRIPTION OF THE INVENTION

Field of the Invention

The invention relates to a starter motor assembly for starting an engine and, more particularly, to a starter motor assembly for starting a vehicle engine that has a solenoid assembly including a pull-in coil comprised of multiple coils connected in parallel.

Background of the Invention

Starter motor assemblies to assist in starting engines, such as engines in vehicles, are well known. The conventional starter motor assembly broadly includes an electrical motor and a drive mechanism. The electrical motor is energized by a battery upon the closing of an ignition switch. The drive mechanism transmits the torque of the electric motor through various components to a flywheel gear of the engine, thereby cranking the engine until the engine starts.

In greater detail, the closing of the ignition switch (typically by turning a key) energizes a solenoid and, in some motors, applies some power to the electrical motor. Energization of the solenoid moves a solenoid shaft or plunger in an axial direction. The movement of the solenoid plunger closes electrical contacts, thereby delivering full power to the electrical motor. The movement of the solenoid plunger also biases a pinion-type gear into engagement with the engine flywheel gear.

Starter motors assemblies can be either "biaxial" or "coaxial." These terms relate to the location of the solenoid and the solenoid plunger with respect to an armature

202-408-4000
WASHINGTON, DC 20005
8 DUNN, L.L.P.
FARABOW, GARRETT,
FINNEGAN, HENDERSON,
LAW OFFICES

20
LAW OFFICES
FINNEGAN, HENDERSON,
FARABOW, GARRETT,
& DUNN, L.L.P.
1300 I STREET, N.W.
WASHINGTON, DC 20005
202-408-4000

shaft of the electrical motor. In a biaxial starter motor, the solenoid and the solenoid plunger are typically attached to the motor casing, with the solenoid plunger spaced away from and generally parallel to the armature shaft. In a coaxial starter motor, the solenoid is typically placed in the motor casing so that the solenoid plunger is aligned in the same axis with the armature shaft. The coaxial assembly is considered to be more compact and universally adaptable than the biaxial assembly. The present invention may be utilized with either a coaxial assembly or a biaxial assembly.

The closing of the electrical contacts in a starter motor assembly applies an electrical current from the battery to the electric motor. The motor's armature shaft subsequently rotates at a high speed. A planetary gear assembly, coupled to the armature shaft, reduces the speed of rotation of the armature shaft. The planetary gear assembly includes a drive shaft that rotates at that reduced speed. The end of the drive shaft opposite the planetary gear assembly is coupled with a pinion, preferably by a pinion shaft. Thus, the pinion rotates due to the rotation of the drive shaft of the planetary gear, which in turn rotates (again, at a reduced speed) due to the rotation of the armature shaft.

Energization of the solenoid also moves the solenoid plunger in an axial direction to bias the pinion into engagement with the engine flywheel gear. The plunger is coupled with the pinion such that the movement of the plunger in turn biases the pinion in an axial direction. In a coaxial assembly, the pinion is aligned in the same axis with the solenoid plunger such that the pinion is biased in the same axial direction that the plunger is biased. In a biaxial assembly, typically a lever is utilized to couple the plunger with the pinion such that the pinion is biased in the opposite axial direction that

LAW OFFICES

FINNEGAN, HENDERSON,
FARABOW, GARRETT,
& DUNNER, L.L.P.
1300 I STREET, N.W.
WASHINGTON, DC 20005
202-408-4000

the plunger is biased. More particularly, a first end of the lever is coupled with the plunger and a second opposite end of the lever is coupled with the pinion. The biasing action of the plunger against the first end of the lever biases the first end of the lever in an axial direction so that the lever rotates in a clockwise or counter-clockwise direction.

- 5 This rotational movement causes the second end of the lever to bias the pinion in the opposite axial direction from that of the plunger.

The pinion typically includes a plurality of teeth or splines on its external surface for engagement with the engine flywheel gear, which also includes teeth or splines to engage with the pinion splines. Thus, when the pinion is biased toward engagement of the flywheel and is rotating, the engagement of the pinion with the flywheel in turn causes the flywheel to rotate, thereby cranking the vehicle engine.

Once the vehicle engine is started, the operator of the vehicle then will open the ignition switch, which deenergizes the solenoid assembly. As a result of this deenergization, the magnetic field that caused the plunger to move decreases and at some point is overcome by a return spring. In particular, the return spring continually biases the pinion away from engagement with the engine flywheel. However, it is only at those times when the force of the return spring is greater than the magnetic field generated by the solenoid biasing the plunger toward the flywheel that the pinion is biased away from engagement from the flywheel.

20 For the energization of the solenoid assembly to move the solenoid plunger and hold the plunger for pinion-flywheel engagement, solenoid assemblies typically utilize two coils, a pull-in coil and a hold-in coil. In particular, both coils energize the plunger of the solenoid assembly to bias the plunger in the axial direction for engagement with the

LAW OFFICES

FINNEGAN, HENDERSON,
FARABOW, GARRETT,
& DUNNER, L.L.P.
1300 I STREET, N. W.
WASHINGTON, DC 20005
202-408-4000

engine flywheel. The hold-in coil then holds the plunger in place to hold the pinion in the engagement position with the flywheel.

Conventional solenoid assemblies typically utilize a single pull-in coil and a single hold-in coil. As shown in FIG. 1, a conventional solenoid assembly includes a solenoid coil holder 118, in which a single pull-in coil 122 is formed of a single, continuous wire coiled and looped up and down the length L of holder 118. The pull-in coil 122 is shown having four layers 200, 202, 204, and 206 of increasingly greater diameter. The pull-in coil 122 is also shown being looped twice within the length L of the holder 118. In other words, the wire comprising the pull-in coil is wound down the length L to form layer 200, then is wound back up the length L to form layer 202, then is wound back down the length L to form layer 204, and finally wound back up the length L to form layer 206. Similarly, a single hold-in coil 124 is coiled and looped up and down the length L of holder 118 to form layers 230 and 232.

FIGS. 2 through 4 are circuit diagrams illustrating the sequence of starting a starter motor including the conventional single pull-in coil in the solenoid assembly. As shown, the electrical circuit 10 of the starter motor includes an ignition switch 12, a battery 14, a motor 30, and a solenoid assembly 100. In particular, the solenoid assembly 100 includes a pull-in coil 122, a hold-in coil 124, and a plunger 113.

FIG. 2 illustrates that point in time before ignition switch 12 is closed. At this point in time, coils 122, 124 are not energized, no electrical current is traveling through motor 30, and plunger 113 is not magnetized and, thus, not biased in an axial direction.

FIG. 3 illustrates that point in time when ignition switch 12 is closed, thereby energizing pull-in coil 122 and hold-in coil 124. Energization of coils 122, 124 in turn

LAW OFFICES

FINNEGAN, HENDERSON,
FARABOW, GARRETT,
& DUNNER, L.L.P.
1300 I STREET, N.W.
WASHINGTON, DC 20005
202-408-4000

biases plunger 113 to move in an axial direction to effect the closing of a plunger contact 142 and two fixed contacts 144 between battery 14 and motor 30 to deliver full power to motor 30 from battery 14. Typically, plunger contact 142 is a copper washer and fixed contacts 44 are the heads of copper bolts.

5 FIG. 4 illustrates that point in time when plunger 113 is biased in the axial direction sufficiently to close contacts 142, 144 between battery 14 and motor 30, thereby delivering full power to motor 30 from battery 14. Once plunger 113 closes the contacts 142, 144, pull-in coil 122 is bypassed or short-circuited as shown in FIG. 4.

10 The pull-in coil and the hold-in coil are typically made of insulated wound wire, wrapped in a coil shape. The pull-in coil is generally an intermittent-duty coil, which is generally energized only for that period of time that it takes for the solenoid plunger to be biased in the axial direction to a seated position for pinion-flywheel engagement. Therefore, the pull-in coil is typically a high magnetomotive force, high heating coil. On the other hand, the hold-in coil is generally a continuous-duty coil, which is generally
15 energized for the entire time that the ignition switch is closed in order to hold the plunger for pinion-flywheel engagement. Therefore, the hold-in coil is typically a low magnetomotive force, low heating coil.

20 The magnetomotive force of the two coils add together to pull the plunger at large air gaps, when the reluctance of the magnetic circuit is highest. During the hold-in phase (*i.e.*, during cranking of the engine), the air gap in the magnetic circuit is very small. Therefore, the reluctance of the magnetic circuit is low, and only a relatively small magnetomotive force is required to hold the plunger for pinion-flywheel engagement. Because only a small magnetomotive force is required to hold the plunger

LAW OFFICES

FINNEGAN, HENDERSON,
FARABOW, GARRETT,
& DUNNER, L.L.P.
1300 I STREET, N.W.
WASHINGTON, DC 20005
202-408-4000

for pinion-flywheel engagement, unwanted heating from the pull-in coil is eliminated by short circuiting this coil when the contacts close to start the motor, as discussed above.

In certain motors, motor 30 does not start until contacts 142, 144 close. In other motors, motor 30 starts before contacts 142, 144 close. For these latter motors, FIG. 3 illustrates that pull-in coil 122 is grounded through motor 30 such that, after ignition switch 12 is closed but before contacts 142, 144 close, any current flowing through pull-in coil 122 (I_1) is equal to the current flowing through motor 30 (I_m). If the resistance of pull-in coil 122 is low enough, then the current flowing through motor 30 (I_m) will be large enough to cause motor 30 to "soft start," thereby providing a rotation of the armature shaft (not shown) of motor 30 that is sufficient to overcome friction and turn the pinion (also not shown). These motors make use of this "soft start" to engage the pinion with the engine flywheel gear. When the solenoid plunger forces the pinion in the axial direction towards engagement with the engine flywheel gear, a tooth on the pinion may hit a tooth on the flywheel gear and fail to engage. In these motors, there is typically a rigid connection between the solenoid plunger and the pinion. Thus, if the pinion stops moving, then the plunger will stop moving. Therefore, if the pinion teeth fail to engage with the flywheel gear teeth, then the plunger is prevented from being biased in the axial direction to close contacts 142, 144 to deliver full power to motor 30. However, if the current flowing through motor 30 (I_m) is large enough, *i.e.*, if the resistance of pull-in coil 122 is low enough, then there will be sufficient motor torque for the pinion teeth to clear the abutment and engage with the engine flywheel gear teeth, thereby allowing closure of contacts 142, 144 to deliver full power to motor 30.

LAW OFFICES

FINNEGAN, HENDERSON,
FARABOW, GARRETT,
& DUNNER, L.L.P.
1300 I STREET, N. W.
WASHINGTON, DC 20005
202-408-4000

In motors that "soft start," pull-in coil 122 generally must be comprised of a large diameter wire to have low resistance to allow sufficient current to motor 30, which again is in series with pull-in coil 122, to clear the tooth abutment between pinion and flywheel gear to close contacts 142, 144 to deliver full power to electric motor 30. The pull-in coil
5 in motors that "soft start" generally comprises a single wire of a large diameter, typically on the order of 2.2 millimeters.

However, pull-in coils that have large diameters suffer several disadvantages. One disadvantage is that the large diameter wire is difficult to wind into a coil shape. In particular, the diameter of the wire is often beyond the limits of most conventional
10 winding equipment, and the wire has a strong tendency to spring back from its wound shape. Also, large bend radii are required for large diameter solenoid lead wires. This fact, along with the tendency of the wire to spring back from its wound shape, makes it difficult to make sharp turns when routing the wires to their termination points.

Another disadvantage is that, when wound, there are large air gaps between the
15 coils of the wound wire, which results in less efficient heat transfer and may increase the size of the pinion housing of the starter motor assembly.

SUMMARY OF THE INVENTION

The present invention is directed to a solenoid assembly for a starter motor
20 assembly including a plurality of individual coils connected in parallel to form a pull-in coil. In one embodiment, the plurality of coils comprises three coils. The plurality of coils are formed from a single wire cut and connected to form the pull-in coil. In addition, after the single wire is cut, each of the coils has a first lead and a second lead,

and the first leads of each coil are connected together and the second leads of each coil are connected together. In one embodiment, the single wire is about 1.0 millimeters to about 1.5 millimeters in diameter.

The present invention is also directed to a solenoid assembly for a starter motor
5 assembly including a pull-in coil comprised of three individual coils connected in parallel. The three individual coils are formed from a single wire cut at two points and then connected to form the pull-in coil. After the wire is cut at two points, each of the three coils has a first lead and a second lead, and the three individual coils are connected to form the pull-in coil by connecting the first leads of each coil together and
10 connecting the second leads of each coil together. In one embodiment, the single wire is about 1.0 millimeters to about 1.5 millimeters in diameter.

The present invention is also directed to a pull-in coil for a solenoid assembly for a starter motor assembly comprising multiple coils connected in parallel. The pull-in coil may be comprised of three coils. The three coils are formed from a single wire that is
15 cut at two points to form the three coils. After the wire is cut at two points, each of the three coils has a first lead and a second lead, and the first leads of each coil are connected together and the second leads of each coil are connected together.

The present invention is also directed to a method of making a pull-in coil for a solenoid assembly for a starter motor assembly comprised of the following steps. First,
20 a wire is wound down a length of a solenoid coil holder and then back up the length of the solenoid coil holder a plurality of times. Then, the wire is cut at points to form separate coils, each coil then having a first lead and a second lead opposite the first lead. Then, the first leads of the coils are electrically connected together and the

LAW OFFICES

FINNEGAN, HENDERSON,
FARABOW, GARRETT,
& DUNNER, L.L.P.
1300 I STREET, N.W.
WASHINGTON, DC 20005
202-408-4000

second leads of the coils are electrically connected together to form the pull-in coil. The wire may be wound down and back up the length of the solenoid coil holder three times and, if so, the wire is cut at two points. In one embodiment, the wire is about 1.0 millimeters to about 1.5 millimeters in diameter.

5 In one embodiment, the leads are electrically connected together by tying the first leads together and tying the second leads together. In an alternative embodiment, the leads are electrically connected together by twisting the first leads together and twisting the second leads together. In another alternative embodiment, the leads are electrically connected together by soldering the first leads together and soldering the second leads
10 together. In another alternative embodiment, the leads are electrically connected together by crimping the first leads together and crimping the second leads together.

The present invention is also directed to a method of making a pull-in coil for a solenoid assembly for a starter motor assembly comprised of the following steps. First, a wire is wound down a length of a solenoid coil holder and then back up the length of
15 the solenoid coil holder three times. Then, the wire is cut at two points to form separate coils, each coil then having a first lead and a second lead opposite the first lead. Then, the first leads of the coils are electrically connected together and the second leads of the coils are electrically connected together to form the pull-in coil. In one embodiment, the wire is about 1.0 millimeters to about 1.5 millimeters in diameter. The leads may be
20 electrically connected together as discussed above.

The present invention is also directed to a method of making a pull-in coil comprised of multiple coils connected in parallel for a solenoid assembly for a starter motor assembly comprised of the following steps. First, a solenoid coil holder is

LAW OFFICES

FINNEGAN, HENDERSON,
FARABOW, GARRETT,
& DUNNER, L.L.P.
1300 I STREET, N.W.
WASHINGTON, DC 20005
202-408-4000

provided that has a first side and a second side opposite the first side. The first and second sides define a length of the solenoid coil holder. Then, a wire is wound down the length of the solenoid coil holder beginning at the first side of the solenoid coil holder and then back up the length of the solenoid coil holder ending at the first side of the solenoid coil holder. The wire is wound down and back up the length of the solenoid coil holder at least three times. Then, the wire is cut at at least two points to form separate coils. Each coil then has a first lead and a second lead opposite the first lead. Then, the first leads of the coils are electrically connected together and the second leads of the coils are electrically connected together to form the pull-in coil.

The present invention is also directed to a method of making a pull-in coil comprised of multiple coils connected in parallel for a solenoid assembly for a starter motor assembly comprised of the following steps. First, a solenoid coil holder is provided that has a first side and a second side opposite the first side. The first and second sides define a length of the solenoid coil holder. Then, a wire is wound down the length of the solenoid coil holder beginning at the first side of the solenoid coil holder and then back up the length of the solenoid coil holder ending at the first side of the solenoid coil holder. Then, the wire is looped outside the solenoid coil holder to form a first loop outside the solenoid coil holder. Next, the wire is wound down and back up the length of the solenoid coil holder a second time. Then, the wire is looped outside the solenoid coil holder a second time to form a second loop outside the solenoid coil holder. Next, the wire is wound down and back up the length of the solenoid coil holder a third time. Then, the wire is cut at two points, with one point being along the first loop and the second point being along the second loop. This forms

separate coils, each coil then having a first lead and a second lead opposite the first lead. Then, the first leads of the coils are electrically connected together and the second leads of the coils are electrically connected together to form the pull-in coil. In one embodiment, the wire is about 1.0 millimeters to about 1.5 millimeters in diameter.

- 5 The leads of the coils may be electrically connected together as discussed above.

The advantages of the invention will be set forth in the description below, and in part will be apparent from the description, or may be learned by practice of the invention. The advantages of the invention may be realized and obtained by the combinations set forth in the attached claims.

- 10 Additional objects and advantages of the invention will be set forth in part in the description which follows, and in part will be obvious from the description, or may be learned by practice of the invention. The objects and advantages of the invention will be realized and attained by means of the elements and combinations particularly pointed out in the appended claims.

- 15 It is to be understood that both the foregoing general description and the following detailed description are exemplary and explanatory only and are not restrictive of the invention, as claimed.

- The accompanying drawings, which are incorporated in and constitute a part of this specification, illustrate several embodiments of the invention and together with the
20 description, serve to explain the principles of the invention.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a cross-sectional view of the windings of a single pull-in coil and a single hold-in coil for a conventional solenoid assembly;

LAW OFFICES

FINNEGAN, HENDERSON,
FARABOW, GARRETT,
& DUNNER, L.L.P.
1300 I STREET, N. W.
WASHINGTON, DC 20005
202-408-4000

FIGS. 2 through 4 are circuit diagrams for the sequence of starting a conventional starter motor assembly including a single pull-in coil;

FIGS. 5 through 7 are circuit diagrams for the sequence of starting a starter motor assembly of the present invention including a pull-in coil comprised of three parallel coils;

FIGS. 8 through 11 are sequential side views of the method of making one embodiment of a solenoid assembly of the present invention including a pull-in coil comprised of three parallel coils in a solenoid coil holder; and

FIG. 12 is a side view of one half of the solenoid coil holder illustrated in FIG. 11, also including a single hold-in coil.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Reference will now be made in detail to the present preferred embodiments of the invention, examples of which are illustrated in the accompanying drawings.

Wherever possible, the same reference numbers will be used throughout the drawings to refer to the same or like parts.

This description will not focus on the particular aspects of utilizing a starter motor to energize a solenoid assembly to (1) start an electrical motor to turn a pinion and (2) bias the pinion into engagement with a engine flywheel to crank the engine. These aspects were discussed above and, to the extent not discussed above, are known in the art. Instead, the focus is on the particulars of the present invention, namely, a starter motor assembly having a solenoid assembly having a pull-in coil comprised of multiple coils in parallel.

FIG. 12 is a side view of one half of the solenoid coil holder illustrated in FIG. 11, also including a single hold-in coil.

LAW OFFICES

FINNEGAN, HENDERSON,
FARABOW, GARRETT,
& DUNNER, L.L.P.
1300 I STREET, N. W.
WASHINGTON, DC 20005
202-408-4000

The present invention is directed to a solenoid pull-in coil which is comprised of a plurality of individual smaller diameter wires formed as a plurality of coils electrically connected in parallel, rather than a single pull-in coil comprised of a large diameter wire coil. The conventional single large diameter wire pull-in coil is discussed above and is shown schematically in FIG. 1 and by sequential circuit diagrams in FIGS. 2-4.

In one embodiment of the present invention, the pull-in coil includes three separate coils connected in parallel. The pull-in coil, however, is not limited to three parallel coils, but may comprise any number of parallel coils. For sake of convenience, however, a pull-in coil comprised of three separate coils will be discussed.

Furthermore, the pull-in coil of the present invention is not limited to any specific type of starter motor assembly, such as a biaxial assembly, a coaxial assembly, or any other configuration.

FIGS. 5-7 illustrate circuit diagrams for the sequence of starting a starter motor assembly of the present invention utilizing three coils for the pull-in coil of the starter motor assembly. As shown in FIGS. 5-7, the electrical circuit 10 of the starter motor includes ignition switch 12, battery 14, motor 30, and solenoid assembly 100, including pull-in coil 122 comprised of three coils 160, 162, and 164, hold-in coil 124, and plunger 113.

FIG. 5 illustrates that point in time before ignition switch 12 is closed. At this point in time, coils 160, 162, and 164 of pull-in coil 122, as well as hold-in coil 124, are not energized, no electrical current is traveling through motor 30, and plunger 113 is not magnetized and, thus, not biased in an axial direction. FIG. 6 illustrates that point in time when ignition switch 12 is closed, thereby energizing coils 160, 162, and 164 of

where:

"1" denotes the conventional single pull-in coil

"a" denotes the innermost coil (coil 160 (see FIG. 12))

"b" denotes the middle coil (coil 162 (see FIG. 12))

"c" denotes the outermost coil (coil 164 (see FIG. 12))

R_1 = Resistance of the conventional single pull-in coil

R_a = Resistance of the innermost coil of the three coils of the pull-in coil of the present invention

R_b = Resistance of the middle coil of the three coils of the pull-in coil of the present invention

R_c = Resistance of the outermost coil of the three coils of the pull-in coil of the present invention

N_1 = Number of turns of the conventional single pull-in coil

N_a = Number of turns of the innermost coil of the three coils of the pull-in coil of the present invention

N_b = Number of turns of the middle coil of the three coils of the pull-in coil of the present invention

N_c = Number of turns of the outermost coil of the three coils of the pull-in coil of the present invention

I_1 = Current through the conventional single pull-in coil

I_a = Current through the innermost coil of the three coils of the pull-in coil of the present invention

I_b = Current through the middle coil of the three coils of the pull-in coil of the present invention

I_c = Current through the outermost coil of the three coils of the pull-in coil of the present invention

If the number of turns of each of the three coils of the present invention is the same as the number of turns of the single coil of the conventional pull-in coil (i.e., $N_a = N_b = N_c = N_1$), then Equation 2 above becomes:

$$\text{Equation 2: } N_1 I_1 = N_1 (I_a + I_b + I_c)$$

which in turn becomes $I_1 = I_a + I_b + I_c$,

which is automatically satisfied if Equation 1 is satisfied.

In addition, with equivalent resistance between the three coils of the present invention and the conventional single coil pull-in coil, it follows that the voltage drop

U.S. PAT. & TM. OFF. FILED MAR 11 2008
COMM. DIV. U.S. PAT. & TM. OFF.
WASHINGTON, D.C. 20540

uninterrupted method of winding may not be utilized because different wires would be utilized.

FIGS. 8-11 illustrate one method of winding a single wire to form a pull-in coil comprised of three parallel coils, while FIG. 12 illustrates one half of a solenoid coil holder having a single coil for the hold-in coil and three parallel coils for the pull-in coil. Preferably, the coils of pull-in coil are comprised of the same wire, yet are formed in such a manner to form the parallel electrical circuit. In particular, each coil is initially wound in series with the other coils. However, after each coil is wound, a programmable winder creates a loop of wire at the end of a bobbin outside of the solenoid coil holder before continuing to wind the next coil. This allows for an uninterrupted winding process of the wire that will form the three coils of the pull-in coil of the present invention. After all of the coils are wound, the loops are then cut, and the leads of the wires are connected to form the coils in parallel. The coils should generally be laid in series, cut and then connected, and not wound simultaneously. In particular, if the parallel coils are wound simultaneously, such as three wires at once, then the wires may not lay properly and a poor winding fill factor may result.

The method of making a solenoid assembly having three parallel coils for the pull-in coil will now be discussed in more detail, referring to FIGS. 8-11. As shown in FIG. 8, a single small diameter wire 150 is first wound down length L of solenoid coil holder 118 and then back up length L of solenoid coil holder 118 to the same side 119 of the solenoid coil holder 118 at which wire 150 began to be wound, thereby forming two layers 210, 212 of wire. Wire 150 is then wound down and back up the length L of

LAW OFFICES

FINNEGAN, HENDERSON,
FARABOW, GARRETT,
& DUNNER, L.L.P.
1300 I STREET, N.W.
WASHINGTON, DC 20005
202-408-4000

solenoid coil holder 118 two more times, as shown in FIG. 9 (forming layers 214, 216) and FIG. 10 (forming layers 218, 220).

Each coil may comprise a wide variety of number of turns. Generally, each coil includes about 40 turns to about 130 turns. In one embodiment, each coil has a total of about 23 turns per layer and, thus, each coil (comprised of two layers) has about 45 turns. In addition, as discussed above, the number of coils for the parallel pull-in coil is not limited to three and may be two or more than three.

In addition, wire 150 is wound such that at side 119 of solenoid coil holder 118 where the wire winding began, wire 150 is looped around to form the second coil and then, after forming the second coil, looped around again to form the third coil. More particularly, as shown in FIG. 9, after wire 150 is wound up and down length L of coil holder 118 to form layers 210, 212, a loop 154 of wire 150 is positioned outside of coil holder 118 before winding wire 150 up and down length L of coil holder 118 a second time to form layers 214, 216. Similarly, as shown in FIG. 10, after wire 150 is wound up and down length L of coil holder 118 a second time to form layers 214, 216, a loop 156 of wire 150 is positioned outside of coil holder 118 before winding wire 150 up and down length L of coil holder a third time to form layers 218, 220.

Then, after the six layers 210-220 of wire 150 are in place, wire 150 is cut at at least two places along loops 154, 156. For example, as shown in FIG. 10, wire 150 is cut at least at two points 158, 159. At that time, as shown in FIG. 11, wire 150 now comprises three separate coils 160, 162, and 164. Coil 160 is generally comprised of layers 210, 212, coil 162 is generally comprised of layers 214, 216, and coil 164 is generally comprised of layers 218, 220. Each coil 160, 162, and 164 has leads

LAW OFFICES

FINNEGAN, HENDERSON,
FARABOW, GARRETT,
& DUNNER, L.L.P.
1300 I STREET, N. W.
WASHINGTON, DC 20005
202-408-4000

designated by the letter A (*i.e.*, 160A, 162A, and 164A) and leads designated by the letter B (*i.e.*, 160B, 162B, and 164B).

As shown in FIG. 12, in order to form the parallel coil circuit, leads 160A, 162A, and 164A of each coil are electrically connected together and leads 160B, 162B, and 164B of each coil are electrically connected together. One method of electrically connecting the leads is tying them together. Other methods may be used to electrically connect the leads, such as by twisting the leads, soldering the leads together, or crimping the leads together. Electrically connected leads 160A, 162A, and 164A may be connected to node S shown in FIGS. 5-7 to receive current I_1 , whereas electrically connected leads 160B, 162B, and 164B may be connected to node M in FIGS. 5-7 or vice versa.

The solenoid assembly also includes hold-in coil 124 comprised of layers 230, 232 of wire, as shown for example in FIG. 12. One lead 124A of the wire used to create coil 124 may be electrically connected to leads 160A, 162A, and 164A to receive current I_2 , as shown in FIGS. 5-7.

In general, for a certain number N of parallel coil paths in the present invention, the cross-sectional area of the wire may be reduced by a factor of approximately $1/N$. For example, for the above example of three parallel coils for the pull-in coil, the cross-sectional area of the wire (forming all three coils) is approximately $1/3$ of the equivalent single pull-in coil design. Thus, the parallel coils of the pull-in coil of the present invention have the advantage that they may be comprised of a smaller diameter wire than a conventional single coil pull-in coil. The wire of the present invention is generally about 1.0 millimeters to 1.5 millimeters in diameter.

LAW OFFICES

FINNEGAN, HENDERSON,
FARABOW, GARRETT,
& DUNNER, L.L.P.
1300 I STREET, N. W.
WASHINGTON, DC 20005
202-408-4000

One advantage of a smaller diameter wire is that it is easier to wind and allows the use of conventional winding equipment. Another advantage to a smaller diameter wire is that it greatly reduces spring back after forming each layer of each coil. Another advantage is that the wire may be wound tighter, which is more efficient, having less air gaps, less heat dissipation and may result in a smaller package (*i.e.*, smaller pinion housing for the starter motor assembly).

A further advantage of using an equivalent parallel coil group is its design flexibility. When designing any coil, attention should be given to the number of layers in the coil. For ease of manufacture and compact packaging, the beginning and end of each coil should occur on the same side of the coil holder. For optimum space utilization, this means that the number of layers per coil should be as close to an even number as possible, but not over that number. For example, with 1.9 layers in a coil, the winding moves away from the starting point for the first layer and moves back towards it in the last 0.9 layer. If a coil has 2.1 layers, however, the direction of the winding would move away from the starting side for the 0.1 layer and then the winding lead would have to be routed back over that 0.1 layer to come out on the starting side. This adds to the overall dimension of that coil and would create an uneven winding surface for the next coil to be wound (provided this coil was not the outermost coil). In solenoid design, it is typical for the value of the pull-in coil resistance to be given, as well as the available winding space. With the present invention, a different layering option results with each possible choice of the number of parallel coil paths. This improves design flexibility, resulting in a more optimized design.

LAW OFFICES

FINNEGAN, HENDERSON,
FARABOW, GARRETT,
& DUNNER, L.L.P.
1300 I STREET, N. W.
WASHINGTON, DC 20005
202-406-4000

Additional advantages and modifications will readily occur to those of ordinary skill in the art. The invention therefore is not limited to the specific details and embodiments shown and described above. Departures may be made from such details without departing from the spirit or scope of the invention. The scope of the invention is established by the claims and their legal equivalents.

Other embodiments of the invention will be apparent to those skilled in the art from consideration of the specification and practice of the invention disclosed herein. It is intended that the specification and examples be considered as exemplary only, with a true scope and spirit of the invention being indicated by the following claims.

10

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
22